

RNC2

XBOOM RNC2 Party Speaker

6.5" Woofer

Customizable LED Lighting

XBOOM App



CONVENIENCE	
XBOOM App	Yes (iOS/Android)
Multi Color Ring Lighting	Yes
FUNCTION SELECTOR	
USB 1	Yes
AUX IN 2 (RCA)	Yes
Bluetooth	Yes
FM Tuner	Yes
SPEAKER	
Front Speaker System	1Way 2Speaker
Front Speaker Tweeter Unit	2.5" x 1
Front Woofer Unit	6.5" x 1
INPUTS/OUTPUTS	
USB 1	Yes
AUX In (RCA)	Yes
Mic Jack	Yes (6.3mm)
Guitar Input	Yes (6.3mm)
SOUND	
EQ	Standard, Bass Blast+
DJ Effect	Yes (App only)
Mic Echo	Yes
User EQ	Yes

KARAOKE CREATOR	
Mic Volume Control	Yes
Mic Echo Control	Yes
TUNER	
Type	PLL
Band	FM
FM Tuning Range (50kHz/100kHz)	87.5 - 108.0 MHz
Memory/Erase	Yes
PLAYABLE DISC/FILE TYPE	
Playable File Format	MP3, WMA
BLUETOOTH AUDIO FORMAT	
SBC	Yes
AAC	No
POWER	
Standby Mode	Less than 0.5W
Power Requirement	Wide 110/220V

INCLUDED ACCESSORIES	
Remote Control	Yes
Batteries	AAA x 2
FM Antenna	Yes
Simple User Manual	Yes
DIMENSIONS / WEIGHTS	
Size (WxHxD)	11.8" x 15.4" x 12.6"
Main Net Weight	14.9 lbs
Shipping Size (WxHxD)	20" x 14.8" x 14.4"
Shipping Weight	17.9 lbs
WARRANTY	
Limited Warranty	1 Year Parts & Labor
UPC	195174071946
Country of origin	China